

4Port DVI KVM Switch

מק"ט: KVM-DVI-4



תיאור המוצר

Description:

The DVI KVM Switch with built-in sound effect function. It is specially designed for users of PC and Mac with built-in DVI interfaces and loyal fans of SOHO environment and technology, which is well-suited for DVI. This unique type of KVM switch can easily control two computers, which have built-in DVI interfaces, via a DVI display and either a PC or Mac keyboard and mouse. Image distortion due to conversion of analog and digital signals will not be a problem anymore.

Features:

- One USB console controls 4 DVI computers
- Fully compliant with the DVI-Digital and DVI-Analog specification

- DVI interface technology to ensure crisp and clean digital display
- Switch Mode: a. button push b. Keyboard Hot-Key switch c. Mouse switch(need install software)
- Multiplatform support: compatible with all operation platforms PC (Windows, Linux and most others), Mac and Sun
- With audio enabled
- Computer selection via front panel pushbuttons and hotkeys
- Superior video quality - up to 1920 x 1200; DDC2B
- HDCP compliant

Specifications:

4	Computer Connections			
Hotkey, Pushbutton	Port Selection			
x USB Type A Female 1	Keyboard	Console Ports	Connectors	
(x DVI Female (White 1	Video			
x USB Type A Female 1	Mouse			
(x Mini Stereo Jack Female (Green 1	Speaker			
DVI Female 4	Video	KVM Ports		
USB Type B Female 4	Keyboard / Mouse			
Mini Stereo Jack Female 4	Speaker			
x DC Jack 1	Power			
Pushbutton 4	Port			Switches
(Orange) 4	On Line / Selected			LEDs
USB	Keyboard/Mouse		Emulation	
x 1200 ; DDC2B 1920	Video			
seconds 10	Scan Interval			
DC5V, 5.1W	Power Consumption			
50°C~0	.Operating Temp		Environment	
60°C~20-	.Storage Temp			
RH, Non-condensing 80%~0	Humidity			
Metal	Housing		Physical Properties	